

16 Channel controlled Zone Paging Martrix Controller PA-2316



Functional Description


1. With 485 communication interface, support broadcast host control;
2. 16 independent partition selection switches, the partitions can be switched at will, without mutual interference;
3. With 6 power signal inputs,
4. Among them, 4 channels are background music programs, and 2 channels are emergency priority programs; the partition working status is displayed by indicator lights,
5. Green light is background music program, red light is emergency priority;
6. The partition is divided into 4 groups of management, A group manages 1-4 areas, B group manages 5-8 areas, C group manages 9-13 areas, and D group manages
7. 14-16 zones, the maximum output power of each group is 2000W, and the maximum output power of each zone is 600W;
8. Support short circuit trigger to open the whole area function;
9. The equipment adopts double relays and double-cut control circuit at the same time, and the channel isolation is $\geq 80\text{dB}$, which can solve the mutual
10. Problems such as crosstalk;
11. 2U standard chassis design, aluminum alloy panel, beautiful and practical;
12. Emergency short circuit input

Front Panel



- 1. Power Switch 2. Zone Button 3. Zone States Indicator
- 4. All Select Button 5. Switch To Strong Paging State Button
- 6. In Site After Strong Paging Button

Rear Panel



- 1. Emergency Amplifier Input 2. RS485 Control Interface
- 3. 16 division output 4. Amplifier input
- 5. Emergency input 6. Power input socket

Technical Parameter

Item	PA-2316
Input Channel	5
Output Channel	16
Control Mode	Automatic , Manual
On-line Mode	485 bus
Power	50W
Power input	AC220/50Hz
Dimensions	485*390*90mm
Weight	7.5KG

Connection Diagram

